

V30-series TV and Radio Wall Outlet Plates

- Modules pre-assembled into plates
- High quality, fully screened
- Low insertion loss and good isolation
- Wide choice and option to mix modules
- Single, Diplexed, Triplexed and multi options
- Modern styling



| Model | V30-111 | V30-211 | V30-221 | V30-131 | V30-141 | V30-162 | V30-511 |
|------------------------------------|-----------------|-------------------|--------------|-------------|----------------------|--------------------|---------------|
| Description | Single F female | Single IEC female | Diplexed IEC | Triplexed | Triplexed with SAT 2 | Multiservice | RJ11 BT slave |
| Insertion Loss 5-68MHz (Link) | <0.5dB | - | 0.5dB on TV | 0.5dB on TV | 0.5dB on TV | 0.5dB on TV | - |
| Insertion Loss 87.5-230MHz (Radio) | <0.5dB | - | 0.5-1.5dB | 0.5-1.5dB | 0.5-1.5dB | 0.5-1.5dB | - |
| Insertion Loss 450-862MHz (UHF TV) | 0.5-1.0dB | - | 1.0-1.5dB | 1.5-3.0dB | 1.5-3.0dB | 1.5-3.0dB | - |
| Insertion Loss 950-2050 (SAT) | - | 2.0-3.0dB | - | 2.0-4.0dB | 2.0-4.0dB on SAT's | 2.0-4.0dB on SAT's | - |
| DC Pass? | Yes | Yes | Yes on TV | Yes on SAT | Yes on SAT's | Yes on SAT's | - |
| Size | Single | Single | Single | Single | Single | Double | Single |

In the interests of continued product development & improvement, Vision Products (Europe) Ltd reserves the right to change product specifications, design & dimensions. Data correct at time of going to press 23/07/2008.